



- ✓ AUTOMATIC VOLTAGE REGULATION SYSTEM AVR
- ✓ LOW OIL PROTECTION
- ✓ OVERLOADING PROTECTION
- ✓ SHORT CIRCUIT PROTECTION
- ✓ ELECTRIC STARTER WITH BATTERY IN KIT
- ✓ BOSCH SPARK PLUG
- ✓ MULTIFUNCTIONAL DISPLAY
- ✓ DIRECT CURRENT POWER TERMINALS 12V AND SOCKET USB 5V
- ✓ POWER SOCKET 230V/32A HIGH POWER TOOLS CONNECTION
- ✓ COPPER ALTERNATOR WINDING
- ✓ REINFORCED STEEL FRAME
- ✓ EFFICIENT AND RELIABLE ENGINE



8894606

ORIGINAL GERMAN DESIGN 

Code   Model	8894601   PS-25	8894602   PS-33	8894603   PS-33E	8894604   PS-55	8894605   PS-55E	8894606   PS-80E
Maximum power, kVA	2,5	3,3	3,3	5,5	5,5	8
Rated power, kW	2	3	3	5	5	7
Voltage, V~Hz	230~50	230~50	230~50	230~50	230~50	230~50
Starter type	recoil starter	recoil starter	electric starter	recoil starter	electric starter	electric starter
Engine displacement, cc	212	212	212	420	420	445
Engine power, HP	7	7	7	15	15	17
Fuel tank volume, L	15	15	15	25	25	25
Fuel type	regular unleaded gasoline					
Weight, kg	35	39	41	84	85	86